

Slim, smart, and always on.

Sleek. Silent. Relentless. The card is an ultra-thin tracker engineered for the long game, delivering up to 24 Months of uninterrupted performance on a single charge. Built for assets that move across borders or vanish into shadows, it connects to a global Bluetooth crowdsourcing network to provide precise location intelligence, anywhere on Earth.

With a streamlined profile and tool-free 3M adhesive installation, it disappears into your assets—remaining hidden while working around the clock. Whether safeguarding cargo, monitoring high-value goods, or acting as a recovery lifeline for vehicles, the TC30 was made to endure, undetected.

Ideal for:

- ✓ Global asset protection
- ✓ Long-term logistics tracking
- ✓ Vehicle theft recovery
- ✓ Covert deployments requiring extended power





Connectivity	Bluetooth low energy (BLE)
Battery	540mAh Li-MnO2 battery
Battery Life	24 months
Power	Red power button
Dimensions	84.5 x 54.4 x 2.0mm
Weight	16g
Colour	Black
Operating temperature	-20 °C to +60 °C
Range	40 meters
IP rating	IP65
Certification	CE, FCC, RoHS







Netstar STAR*tag* card

Use instructions of STARtag card

Turn on the device: press and hold the button for 5 seconds, the device will beep and turn on.



Open the app or web portal and enter the username and password to view the device.



Turn off the device: Quickly press the button 5 times in a row.



Note: Please do not immerse the battery in water or put it into fire, please do not destroy or force open the battery, the battery is disposable and does not allow charging! To protect the environment, please recycle the used battery.

Important reminders

Battery life time varies depending on individual usage habits.

In order to ensure better dustproof and waterproof, after installation, please be sure to press the upper and lower covers to ensure that the equipment is sealed.

Please do not disassemble the device, improper handling by non-professionals may cause damage to the device.





FCC Compliance Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

NETSTAR

Find out more

Simply visit netstar.co.za to order your new vehicle tracking system.

Call us on 0860 12 24 36 where one of our sales consultants will gladly assist you.

Find out more my.netstar.co.za | onlineleads@netstar.co.za | www.netstar.co.za